












	<p><b>E3PINRD</b>      <b>1 3/4" Adjustable Pinhole with Radius Edges - Adjusts To 45°</b>  Add Flange Style  <b>Lamp:</b>      P3MR, RPN3MR:      50W MR16                   P3MR REMOTE, PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm) Aperture: 2" (51mm)</p>	
	<p><b>E3OVAL</b>      <b>2" Oval - Adjusts To 45°</b>  Add Flange style  <b>Lamp:</b>      P3MR, RPN3MR, P3MR REMOTE:      50W MR16                   PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm)</p>	
	<p><b>E3SA</b>      <b>Super Adjustable 15° - 75° Tilt (Includes Hex cell Louver)</b>  <b>Lamp:</b>      P3MR, RPN3MRSA:      50W MR16                   P3MR REMOTE, PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm)</p>	
<b>3" WALL WASH ELEMENTS</b>		
	<p><b>E3LWW</b>      <b>Lensed Wall Wash</b>  Add Cone Color and Flange style  <b>Lamp:</b>      P3MR, RPN3MR, P3MR REMOTE:      50W MR16                   PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm) Aperture: 3 1/2" (89mm)</p>	
	<p><b>E3AASR</b>      <b>Wet Location Angle Cut Reflector - Adjusts To 45°</b>  Add Cone Color and Flange style  <b>Lamp:</b>      P3MR, P3MR REMOTE, RPN3MR:      50W MR16                   PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm) Aperture: 3 1/2" (89mm)</p>	
	<p><b>E3AASRPIN</b>      <b>Wet Location 2" Adjustable Pinhole - Adjusts To 45°</b>  Add Flange Style  <b>Lamp:</b>      P3MR, P3MR REMOTE, RPN3MR:      42W MR16                   PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm) Aperture: 2" (51mm)</p>	
	<p><b>E3SR</b>      <b>Wet Location 50° Cutoff Reflector</b>  Add Cone Color and Flange style  <b>Lamp:</b>      P3MR, P3MR REMOTE, RPN3MR:      50W MR16                   P3MR REMOTE, PN3MR, PN3MR REMOTE:      71W MR16  <b>Dimensions:</b>      OD: 5 1/8" (130mm) Aperture: 3 1/2" (89mm)</p>	

## ELEMENT OPTIONS

### Cone Finishes:

**C** = Clear Specular Alzak  
**H** = Haze Clear Semi-Specular Alzak  
**G** = Champagne Gold Specular Alzak  
**B** = Specular Black Alzak  
**WMH** = Warm Haze Semi-specular Alzak with a hint of gold to add visual warmth  
**GP** = Graphite Gunmetal grey, specular Alzak  
**GPH** = Graphite Haze Graphite, semi-specular Alzak  
**W** = Gloss White Paint  
**MW** = Matte White  
**K** = Cognac Warm copper color, specular Alzak  
**KH** = Cognac Haze, semi-specular Alzak

### Baffle Options

**BB** = Black Baffle  
**WB** = White Baffle

### Flanges

**Blank** = Matte white die-cast flange ring, removable for field painting  
**RAW** = Die cast trim ring, mill finish  
**SF** = Self Flange (4 7/8" OD) (flange color matches reflector cone) **Not recommended for use with RPN3MR.**  
**SFWF** = Self Flange painted Matte White (4 7/8" OD)

### E3PIN and E3OVAL

**Blank** = Matte White painted die-cast trim ring with black oculus (when present)  
**W** = Matte White painted die-cast trim ring with white oculus (when present)  
**POL** = Polished Aluminum with Black Oculus  
**SAL** = Satin Aluminum with Black Oculus

Example:

**E3MR**

Cone  
Finish

Flange  
Type and  
Finish

Example:

**E3MR**

Baffle  
Finish

Flange Type and  
Finish (self flange  
not available)

Example:

**E3PIN**

Flange Type and  
Finish (self flange  
not available)